

PROformance Series Li-ion Batteries

Charger Compatibility Reference Guide



36V

| Battery Voltage | Battery Model | Charger Model | Charger Power | CAN Integration | Battery Profile | Application Notes |
|-----------------|---------------|--|---------------|------------------|--------------------------|---|
| 36 | S-36V80-TRX | Lester Electrical Summit Series II 650W (30600) | 650W | No Communication | 22743 - v3 | Download algorithm from Lester Charger Connect App |
| | | Lester Electrical Summit Series II 1050W (30410) | 745W | No Communication | 22743 - v3 | Download algorithm from Lester Charger Connect App |
| | | Pro Charging Systems Dual Power 36/12 | 615W | No Communication | Inventus NMC S-36V80-TRX | *Charger must be manufactured after Jan 3, 2023; Download algorithm from ProView Link App |
| | | Delta-Q IC650 36V | 650W | No Communication | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC900 36V | 900W | No Communication | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC1200 36V | 1200W | No Communication | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC650 36V | 650W | J1939 | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC900 36V | 900W | J1939 | Algorithm 29 | Get FW File from Inventus Power |
| 36 | M-36V80-TRX | Lester Electrical Summit Series II 650W (30600) | 650W | No Communication | 22743 - v3 | Download algorithm from Lester Charger Connect App |
| | | Lester Electrical Summit Series II 1050W (30410) | 745W | No Communication | 22743 - v3 | Download algorithm from Lester Charger Connect App |
| | | Delta-Q IC650 36V | 650W | No Communication | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC900 36V | 900W | No Communication | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC1200 36V | 1200W | No Communication | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC650 36V | 650W | J1939 | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC900 36V | 900W | J1939 | Algorithm 29 | Get FW File from Inventus Power |
| | | Delta-Q IC1200 36V | 1200W | J1939 | Algorithm 29 | Get FW File from Inventus Power |

Liability Disclaimer: Inventus Power makes every effort to ensure the safety and compatibility of its products with chargers. However, it is crucial for users to exercise due diligence and responsibility when selecting chargers for their specific needs. Inventus Power assumes no liability for any damage, injury, or malfunction arising from the use of incorrect or unapproved chargers with our products. Additionally, any misuse or programming of the wrong profile or firmware onto the charger that results in adverse outcomes is the sole responsibility of the user, and Inventus Power disclaims any liability in such cases. Users are encouraged to refer to the product's user manual and seek professional guidance when in doubt about charger compatibility or programming. Safety is paramount, and we strongly advise our customers to prioritize it in their charging practices. Please contact Inventus Power's technical support for questions related to compatible chargers or charger battery profile.



**Request
more information**

Inventuspower.com | Info@Inventuspower.com | +1 877.423.4242

Charger Compatibility Guide_Oct-2023_V1